

Lightology

lightology.com
866-954-4489
04-25-26

Project: _____

Company: _____

Location: _____ Fixture Type: _____

SPEC #: **BPU1303208**

Approved On: _____ Approved By: _____

Buster + Punch Complete Metal Dimmer NEW

By Buster + Punch



Description

The Buster + Punch Complete Dimmer is made from solid metal with a diamond cut knurled knob. Works exclusively with the Buster + Punch range of wall plates, dimmer knobs and detail kits. Operates with a push on/off rotary dimmer action for pinpoint dimming accuracy and can be used with single pole or 3-way circuits. The dimmer module has intelligent load matching to enhance compatibility, while minimizing noise and flicker. It can be used on a lighting circuit that powers dimmable LED, low voltage bulbs, LED drivers and it is optimized for use with all Buster + Punch dimmable light bulbs. The dimmer module has a max load of 250W for LED and 300W halogen or incandescent light sources. Fit this dimmer as the only switch on a single-pole circuit, or to control your lighting from two locations on the same circuit, use this dimmer switch and one 3-way on/off switch. The Complete Dimmer includes push On/Off rotary dimmer module compatible with 3-way switching, wall plate, and detail kit. Dimmer has a 1/8 inch shadow gap when installed. Available with or without a Buster + Punch logo. NOTE: This dimmer module is not a 0-10V dimmer and is not compatible with retractive switches, non-dimmable LED lamps, fluorescent and energy-saving bulbs and tubes, electric motors, and fans. Learn more about Buster + Punch Electricity Collection here.

Specifications

COLOR	N/A
BODY FINISH	White
WATTAGE	300W
DIMMER	N/A
DIMENSIONS	2.75"W x 4.75"H x 1.62"D
BULB	N/A
COUNTRY OF ORIGIN	China



Shown in white

ELECTRICAL SPECIFICATIONS

PARAMETER	VALUE
Supply voltage & Frequency	100 - 120V AC 60Hz
Rating	5-250W. When used with dimmable LED lamps, 10-300W. When used with incandescent lamps, halogen lamps and Low Voltage Incandescent Ballasts
Dimming Technology	 Automatic Detection of Forward Phase and Reverse Phase Dimming mode. User Select also available.
Compatible loads for RP MODE - REVERSE PHASE	 Dimmable LED lighting with compatible Electronic Transformers
	 LV Halogen Lighting with electronic transformers
Compatible loads for FP MODE - FORWARD PHASE	 Incandescent lighting, MV Halogen lamps
	 LV Halogen Lighting with iron-core transformers
Operating Temperature	32° - 95° F
Operating Humidity	10-90% RH



CLICK TO VIEW PRODUCT

Notes: