

Lightology

lightology.com
866-954-4489
04-12-26

Project: _____
Company: _____
Location: _____ Fixture Type: _____
SPEC #: **EDG186460**
Approved On: _____ Approved By: _____

300W 12V AC Electronic Transformer By PureEdge Lighting

Description

Standard version 12 Volt remote transformer for AC LED, Incandescent and Halogen bulbs. Features no load technology, isolated output power, soft start, and low profile design. Auto-reset, short circuit, overload and thermal protection. Maximum load: 300 watts. Minimum load: 50 watts. Input: 120 volts, 60 hz. Input current at maximum load: 2.5 amps. Output: 12 volts. Dimmable with low voltage electronic dimmer. UL and cUL listed. 4.1 inch width x 1.55 inch height x 3.2 inch length.

Specifications

COLOR	N/A
BODY FINISH	Black
WATTAGE	300W
DIMMER	Low Voltage Electronic
DIMENSIONS	3.2"L x 4.1"W x 1.55"H
BULB NOT INCLUDED	N/A



Shown in black



CLICK TO VIEW PRODUCT

Notes: