

# Lightology

lightology.com  
866-954-4489  
04-25-26

Project: \_\_\_\_\_

Company: \_\_\_\_\_

Location: \_\_\_\_\_ Fixture Type: \_\_\_\_\_

SPEC #: **WAC23866**

Approved On: \_\_\_\_\_ Approved By: \_\_\_\_\_

## 12V Non-Enclosed Class 2 Electronic Transformer By WAC Lighting



### Description

60 Watt Low Voltage Class 2 120V input/12V output electronic transformer designed to be used as a replacement part for factory installed transformers or installed in a properly listed enclosure. Built-in auto reset, soft start, short and overload circuit protection features. The soft start delayed start feature extends lamp life by delaying the abrupt inrush current to the lamp. Note: 1W minimum load. All connections must be made in an enclosure for proper installations. Dimmable with electronic low voltage dimmers. Dimmers should always be installed on the primary side of the transformer. Optional accessories sold separately.



Shown in black

### Specifications

COLOR	N/A
BODY FINISH	Black
WATTAGE	60W
DIMMER	Low Voltage Electronic
DIMENSIONS	2.38"L x 1.38"W x 1"H
BULB	N/A
COUNTRY OF ORIGIN	China



CLICK TO VIEW PRODUCT

Notes: