

BRAND

Juno Lighting

DESCRIPTION

The Aculux 3ASLOT 3.25 Inch Aperture Slot Angle Cut Cone Trim is compatible with MR16, PAR, and LED housings. MR16 Housing: One 75 watt, 12 volt GU5.3 MR16 halogen lamp or LED equivalent is required, but sold separately. PAR Housing: One 50-75 watt, 120 volt PAR16 or 50 watt, 120 volt PAR20 medium base halogen lamp or LED equivalent is required, but not included. LED Housing: 27 watt, 120 volt 2000 lumen LED module included with housing. 5 inch outside diameter. 3.25 inch aperture. Lamp type and wattage dependent on housing/trim combination. A complete fixture requires a housing and trim, sold separately. Note: This is a discontinued model and limited to quantity on hand.




TRIM COLOR	N/A
BODY FINISH	White / Black Alzak
WATTAGE	8W
DIMMER	Dimmable
DIMENSIONS	3.25"W
BULB NOT INCLUDED	
LAMP	1 x MR16/GU5.3 (bipin)/8W/12V LED 1 x LED/120V LED 1 x PAR16/Medium (E26)/120V Halogen 1 x PAR16/Medium (E26)/120V LED 1 x PAR20/Medium (E26)/120V Halogen

Technical Information

FUNCTION	Adjustable Accent
APERTURE SHAPE	Round
APERTURE SIZE	3.250"

SPEC #	JUN25651
--------	----------

	Construction:	Type IC & Non-IC
	CCT/CRI:	827, 830, 835, 840, 930
	Optic:	S, N, F, W
	Trim Finish:	C, HZ, WHZ

	Construction:	Type IC
	CCT/CRI:	927, 930
	Optic:	S, N, F, W
	Trim Finish:	C, HZ, WHZ

COMPANY	PROJECT	FIXTURE TYPE	APPROVED BY	DATE