

lightology.com 866-954-4489 12-25-25

Project:	
Company:	
Location:	Fixture Type:
	Fixture Type.
SPEC #: LUT6022	
Approved On:	Approved By:

Maestro 450W Magnetic Low Voltage Multi Location Dimmer By Lutron



Description

The Maestro 450W Magnetic Low Voltage Multi Location Dimmer may be used in a multi-location system. Provides true dimming from each location when used with Maestro companion dimmers, sold separately. For use with magnetic low voltage lamping only. Minimum lamp load is 40 watts, maximum lamp load is 450 watts based on assumed 20 percent transformer loss. Rated for a maximum of 600VA. Tap on to reach your favorite light level, and simply tap again to turn off. Tap twice for full on, or touch the rocker to find the perfect light level. Press, hold, and release for delayed fade-to-off. Advanced programming features are available. NOTE: Designer wall plates sold separately.



Shown in gloss white

Specifications

COLOR														Ν	/Α
BODY FINISH											G	los	s V	۷hi	te
WATTAGE													. 4	1 50	W
DIMMER								Lov	v Vc	lta	ıge	· M	ag	net	tic
DIMENSIONS											1.6	"W	X	4.2	"H
BULB														Ν	/Α
COLINITRY OF ODICINI											In		٦ ,		



CLICK TO VIEW PRODUCT

Notes:	