

lightology.com 866-954-4489 11-07-25

Project:	
Company:	
Location:	Fixture Type:
SPEC #: HAD63003	
Approved On:	Approved By:

300 Watt 12-15 Volt Multitap Outdoor Transformer By Hadco by Signify





Description

300 Watt Multitap Magnetic Transformer features 12, 13, 14 and 15 volt output taps for design flexibility and longer cable run capability. .5 inch knockout on one side for hardwiring or accessory mounting. Lockable captive door hinged on side. 6 foot heavy duty power cord with 3 prong grounded wall plug. Thermally protected on primary with secondary side protected by circuit breaker. Euro-Board terminal block for easy low voltage cable attachment. Four .5 inch knockouts for low voltage exit on bottom of housing. One 1.5 inch conduit inlet. Cable entries should be positioned downward. Includes weatherproof compartment for plug in time clock and photocell, sold separately. Transformer should be mounted on the wall, structure or post in the vertical position.



Shown in dark grey

Specifications

COLOR
BODY FINISH
WATTAGE
DIMMER
DIMENSIONS
BULB



CLICK TO VIEW PRODUCT

Notes:	