Lightology

lightology.com
866-954-4489
10-29-26

Project:

Company:

Location: Fixture Type:

SPEC #: **AST882922**

Approved On: Approved By:

7.4-22W 350mA Constant Current Phase Dim LED Driver

By Astro Lighting

Description

The 22 Watt Class 2 350mA Constant Current Phase Dim LED Driver designed for use with Astro Lighting products requiring a driver. Input Voltage: 108-132V AC. 50/60Hz. Minimum Output Voltage: 21.0V DC Maximum Output Voltage: 63.0V DC. Minimum Output Power: 7.35W. Maximum Output Power: 22.05W. ETL listed. Suitable for damp locations. Dimmable with phase leading/trailing edge dimmers, sold separately.



Shown in black

Specifications

COLOR	N/A
BODY FINISH	Black
WATTAGE	22W
DIMMER	Low Voltage Electronic
DIMENSIONS	4.8"W x 1"H x 1.57"D
BULB NOT INCLUDED	N/A
COUNTRY OF ORIGIN	China

CLICK TO VIEW PRODUCT

Notes: