



**BRAND**

Astro Lighting

**DESCRIPTION**

The 22 Watt Class 2 350mA Constant Current Phase Dim LED Driver designed for use with Astro Lighting products requiring a driver. Input Voltage: 108-132V AC. 50/60Hz. Minimum Output Voltage: 21.0V DC Maximum Output Voltage: 63.0V DC. Minimum Output Power: 7.35W. Maximum Output Power: 22.05W. ETL listed. Suitable for damp locations. Dimmable with phase leading/trailing edge dimmers, sold separately.



*Shown in: Black*

<b>SHADE COLOR</b>	N/A
<b>BODY FINISH</b>	Black
<b>WATTAGE</b>	22W
<b>DIMMER</b>	Low Voltage Electronic
<b>DIMENSIONS</b>	4.8"W x 1"H x 1.57"D
<b>BULB NOT INCLUDED</b>	
<b>LAMP</b>	N/A

**SPEC #** AST882922

COMPANY	PROJECT	FIXTURE TYPE	APPROVED BY	DATE