

# Lightology

lightology.com  
866-954-4489  
06-04-26

Project: \_\_\_\_\_


Company: \_\_\_\_\_

Location: \_\_\_\_\_ Fixture Type: \_\_\_\_\_

SPEC #: **AST882923**

Approved On: \_\_\_\_\_ Approved By: \_\_\_\_\_

## 16W 350mA Constant Current 0-10V Dim LED Driver By Astro Lighting



### Description

The 16 Watt Class 2 350mA Constant Current 0-10V Dim LED Driver is designed for use with Astro Lighting products requiring a driver. Input Voltage: 120-277V AC. 50/60Hz. Minimum Output Voltage: 15.0V DC Maximum Output Voltage: 46.0V DC. Minimum Output Power: 5.25W. Maximum Output Power: 26.10W. ETL listed. Suitable for damp locations. Dimmable with a 0-10V dimmer, sold separately.



Shown in black

### Specifications

COLOR	N/A
BODY FINISH	Black
WATTAGE	16W
DIMMER	0-10V
DIMENSIONS	3.12"W x 3.02"H x 1"D
BULB NOT INCLUDED	N/A
COUNTRY OF ORIGIN	China



CLICK TO VIEW PRODUCT

Notes: