



BRAND PureEdge Lighting

DESCRIPTION

The IOTA IIS-50-I is a sine wave output inverter designed to provide power to the designated emergency lighting fixture. In a power loss situation, the IOTA IIS-50-I will supply 120 or 277 VAC power to operate up to a 50W total connected load for not less than 90 minutes. The IOTA IIS- 50-I works in conjunction with LED, fluorescent, and incandescent lamp and fixture types and will automatically run switched, normally-on, or normally-off designated emergency fixtures. The IIS-50-I is ideal for applications requiring an emergency source in elevated ceilings, for high output luminaires, and lamp types utilizing Edison screw (ES) designs. The IIS-50-I features a replaceable long-life nickel-cadmium battery and is covered under IOTA's five-year warranty. Rated for damp locations. UL listed.



Shown in: Black

SHADE COLOR	N/A
BODY FINISH	Black
WATTAGE	50W
DIMMER	N/A
DIMENSIONS	22.5"W x 3"H x 2.75"D
LAMP	N/A
SPEC #	EDG891173

COMPANY	PROJECT	FIXTURE TYPE	APPROVED BY	DATE