Lightology

lightology.com
866-954-4489
10-29-26

Project:

Company:

Location: Fixture Type:

SPEC #: **ELE9453**

Approved On: Approved By:

# 300W 12V Remote Magnetic Transformer


By Visual Comfort Architectural

## Description

This 300 watt 12 volt remote magnetic transformer converts standard 120 or 277 volt line voltage to 12 volts, providing the necessary voltage for powering a Tech Lighting low voltage lighting system. Can be used to power lamps totaling up to 300 watts. This transformer is equipped with fast-acting short circuit and overload protection that will safely turn off the system should a short occur. Once the short is removed, the unit can be reset. Must be installed in a remote, but accessible location such as above the ceiling or a closet, and should be located no more than 20 feet from the required single feed power feed, sold separately. ETL listed.



Shown in black




**Specifications**

| | |
|---|---|
| COLOR | N/A |
| BODY FINISH | Black |
| WATTAGE | 300W |
| DIMMER | Low Voltage Magnetic |
| DIMENSIONS | 10.6"L x 4.3"W x 4.1"H |
| BULB | N/A |

CLICK TO VIEW PRODUCT

Notes: