Lightology

lightology.com
866-954-4489
10-30-26

Project:

Company:

Location: Fixture Type:

SPEC #: **ELE9453**

Approved On: Approved By:

300W 12V Remote Magnetic Transformer


By Visual Comfort Architectural

Description

This 300 watt 12 volt remote magnetic transformer converts standard 120 or 277 volt line voltage to 12 volts, providing the necessary voltage for powering a Tech Lighting low voltage lighting system. Can be used to power lamps totaling up to 300 watts. This transformer is equipped with fast-acting short circuit and overload protection that will safely turn off the system should a short occur. Once the short is removed, the unit can be reset. Must be installed in a remote, but accessible location such as above the ceiling or a closet, and should be located no more than 20 feet from the required single feed power feed, sold separately. ETL listed.



Shown in black



Specifications

COLOR	N/A
BODY FINISH	Black
WATTAGE	300W
DIMMER	Low Voltage Magnetic
DIMENSIONS	10.6"L x 4.3"W x 4.1"H
BULB	N/A

CLICK TO VIEW PRODUCT

Notes: