

Lightology

lightology.com
866-954-4489
05-17-26

Project: _____

Company: _____

Location: _____ Fixture Type: _____

SPEC #: **AST966270**

Approved On: _____ Approved By: _____

12W 500mA Constant Current Phase Dim LED Driver

By Astro Lighting



Description

The 12 Watt Class 2 500mA Constant Current Phase Dim LED Driver is designed for use with Astro Lighting products requiring a driver. Input Voltage: 108-132V AC. 50/60Hz. Minimum Output Voltage: 5.0V Maximum Output Voltage: 17.0V. Minimum Output Power: 2.5W. Maximum Output Power: 12W. Suitable for damp locations. Dimmable with leading/trailing edge dimmers, sold separately.



Shown in black

Specifications

COLOR	N/A
BODY FINISH	Black
WATTAGE	12W
DIMMER	Low Voltage Electronic
DIMENSIONS	4.86"W x 0.79"H x 1.3"D
BULB NOT INCLUDED	N/A
COUNTRY OF ORIGIN	China



CLICK TO VIEW PRODUCT

Notes: