

# WAC LIGHTING

## Under Cabinet Strip

### Transformers

Fixture Type: \_\_\_\_\_  
Catalog Number: \_\_\_\_\_  
Project: \_\_\_\_\_  
Location: \_\_\_\_\_

Model	Max Output Power	Product	L x W x H
○ LU-2420D-P-BK	20	Plug-in Electronic Transformer 100-240V Input 24V Output 20W	2.75IN x 1.625IN x 1.125IN
○ LU-2420D-P-WT	60		4IN x 2.1875IN x 1.5IN
○ LU-2460D-P-BK	96	Plug-in Electronic Transformer 120V Input 24V Output 60W Remote Electronic Transformer 100-277V Input 24V Output 60W Remote Electronic Transformer 100-277V Input 24V Output 96W	8.8125IN x 2.0625IN x 2.25IN
○ LU-24DC060-UNV-RB2			
○ LU-24DC096-UNV-RB2			

Example: **LU-2420D-P-BK**

#### DESCRIPTION

Low Voltage Class 2 electronic transformer designed to be used as a plug-and-play style transformer. Contains a 72" cord with a quick connect. Inherently protected and power limited, protecting the lighting system from both normal and abnormal short circuits. Built-in auto reset, soft start, short and overload circuit protection features. The soft start delayed start feature extends lamp life by delaying the abrupt inrush current to the lamp. Ideal for WAC Lighting under cabinet systems.

#### FEATURES


- Includes 6' lead wire and live end
- LU-2460D-P-BK : Integral On/Off switch
- 5 year warranty

#### SPECIFICATIONS

<b>Input:</b>	100-240 VAC,100-277 VAC,120 VAC,50/60HzHz
<b>Dimming:</b>	ELV: 100-10% , TRIAC: 100-10%
<b>Rated Life:</b>	50,000 Hours
<b>Finish:</b>	Electrostatically Powder Coated: Black, White,
<b>Operating Temp:</b>	-4°F to 104°F (-20°C to 40°C)
<b>Standards:</b>	UL, cUL, Damp Location Listed



#### FINISHES:



Black

White

# WAC LIGHTING

## Under Cabinet Strip

Transformers

Fixture Type: \_\_\_\_\_  
Catalog Number: \_\_\_\_\_  
Project: \_\_\_\_\_  
Location: \_\_\_\_\_

### LINE DRAWING:

